

## SOLUS RFM40



The SOLUS RFM40 pulse-listening mono system is a Retail Loss Prevention system that offers premium security in a modern and solid jacket, designed and optimized for maximum performance in supermarkets, hypermarkets and DIY stores.

The SOLUS RFM40 has a reinforced base-frame and is supplied with an XL base plate with four additional mounting holes, which will ensure proper fixation to any floor type.

The SOLUS RFM40 offers remote connectivity, which enables direct insight in store and system performance. Automatically generated reports can be sent to your mailbox and information can be easily integrated into existing management information systems.

Remote maintenance guarantees optimum operation at minimum cost.

### Unique features

---

Premium detection combined with maximum transparency

---

Selectable notifications for different alarm types

---

Remote service enabled

---

Transparent panels and advertising panels optionally available

---

Shielding plate optionally available

---



# SOLUS RFM40 Antenna Line

## Features

### SOLUS RFM40 Luna

Anodized aluminum frame	●
Premium detection in challenging environments	●
Remote service and management information <sup>1</sup>	●
Selectable notifications for different alarm types	●
Bi-color alarm lights (red & green)	●
Jammer detection	●
Transparent panels	○
Advertising panels	○
Additional features through add-ons	○
Shielding plate	○

## Detection distance <sup>2</sup>

Cross Point OSTRA D55 hard tag (Ø 55 mm)	up to 1.15 m
Cross Point OSTRA D50 hard tag (Ø 50 mm)	up to 1.10 m
Cross Point OSTRA D40 hard tag (Ø 40 mm)	up to 1.05 m
4 x 4 cm paper label	up to 1.00 m

## Specifications

Antenna width	380
Antenna height	1587
Antenna depth (base / profile mm)	100 / 53
Mains (VAC)	100 – 230
Board power (VDC)	15
Power over field bus	●
Programmable I/Os / Relays	2 / 1

1. In combination with the CrossCONNECT Access Point

2. Tested with Cross Point tags in side and flat carry orientations, depending on environment. The specified distance is on each side of the antenna. When a shielding is placed, the specified distances will be reduced.